

Wireless Infrared Barrier



Plus Model: AH-801J(Wireless Convert), enable to convert wireless signal to wired output(NC/NO).



433MHZ/868MHZ



Fuzzy Logical Technology



Detection Range:10m



Endurance :4years



Million Coding Chipset



One Step Installation

Wireless Barrier ABI10-654W



Features

All wireless transmission
New generation for active barrier.

Low voltage design
One piece of battery lasts 4 years lifetime.

Intelligent fuzzy logical technology
Say bye to false alarm.

Weatherproof IP66
Easy to deal with all kinds of bad weather

High level safety
Built in million coding chipset

Convenient for installation
One step for power on & beam alignment.

Parameters

- Standby current : TX<60uA ; RX<100uA
- Current consumption : 0.3mA
- Battery endurance : 4 years
- Triggering : Interruption of upper or below two infrared beams,or all four infrared beams
- Interruption time : ≥40ms
- Max detection range : 10m
- Wireless transmitting distance : 100m(no obstacle)
- Wireless frequency : 433MHZ
- Weatherproof : IP66
- Dimension:39*39*648.3mm